

12 Volt DC Transformer - Power Supply

Power source for stand-alone applications that do not pull from an alarm. It can be used for Winland's wireless transmitters (EA-WTS, EA-WHS and EA-WMFS), the barrel connector can also be snipped off and the wires stripped then used with Winland's EnviroAlert Consoles (EA200, EA400 and EA800-ip), or Winland's Waterbug devices (WB200 and WB800). NOTE: the positive wire is deonted with a gray stripe.



Specifications

Input	120VAC @ 1A
Output	12VDC @ 500mA
Load Regulation	12 VDC \pm 5% @ <500mA
Installing	Gray Stripe on cable = positive (+)
Cable Length	4.75' (1.45 m)
Operating Temp	32° to 104° F (0° to 40° C)
Dimensions	2.25 x 1 x 2.5" (63 x 43 x 26.6 mm)
Weight	2.40 oz (68.04 g)



Visit www.winland.com, call 800.635.4269 or email techsupport@winland.com to learn more.